

TS1162

3-LED Keypad with Request to Exit



Overview

The keypad may be connected directly to the Challenger RS-485 LAN, up to 1.5 km from the Challenger panel or Intelligent Access Controller. It has an input for request to exit (RTE) control and an open collector output that can be used to control a door relay or door strike.

Communication

The keypad's performance and robust construction make it suitable for a wide range of applications, including dusty or wet environments (rated to IP67). It may be used as a Challenger system remote arming station.

Design

The unique design of the housing allows the keypad to be used in the most demanding surroundings. It can be installed directly onto a metal surface without insulation.

Features

- Robust moulded plastic housing
- Indoor or outdoor mounting
- Request to Exit input
- Open collector output (door relay/strike)
- IP67 rating

Interlogix
National Sales Enquiries
1300 361 479

Level 1
271-273 Wellington Road
Mulgrave, Victoria 3170
T +61 3 9239 1200
F +61 3 9239 1298

Specifications subject to change without notice.

© 2013 Interlogix.
All rights reserved.
Interlogix is part of UTC Climate, Controls & Security,
a unit of United Technologies Corporation.

Specifications & Ordering Information

Specifications

Input power	10.8 to 30 VDC
Current consumption	130 m A max.
Material of design housing	Plastic
Dimensions (WxHxD)	4 x 140 x 20 mm
Operating temperature	-40 to +55 C
Storage temperature	-40 to +55 C
IP rating	IP67
Cable	2 m LiYY (included)
Addressing	Via keypad
EMC	C-Tick
Pry-off tamper	Optical sensor
Open collector output	10 mA max

Ordering Information

TS1162	3-LED weather-resistant keypad
--------	--------------------------------

www.interlogix.com.au